

QSSM-3114 (HDMI 2.0)

QSSP-3114 (4K DP)

4 Ports True 4K KVM Switch with Seamless Switch, Serial Control, Keypad IN, USB 3.2 Gen 1



QSSP-3114



QSSM-3114

Features

- Allows 4 Computers Sharing 1 Set of KVM Console
- Most Popular Resolution Supported** Up to 4K@60Hz, & 16:9 / 21:9 / 32:9 Aspect Ratios
- Seamless Switching** Grants the Best Productivity
- HDCP 2.2 / 1.4 Compliance** Ensures Uninterrupted Video Playback
- HDR10 Compliance** Gives the Best Visual Experience
- Continuous & Unified** Video Output Minimizes the Start-Up Procedure
- Flexible Control Methods Suits Variable Scenarios :
 - Push Button - Keyboard Hotkey
 - Serial Control - Keypad Control
- Serial Control** Facilitates Industrial Control Purposes (8-Bands Baud Rate Selectable)
- Keypad IN** Supports Wired & Wireless USB Keypad, and Allows Controlling the KVM Remotely
- DP Model Equipped with an Extra HDMI Output (QSSP-3114)
- Output Scaling Function** Facilitates Connection to Projector / KVM Extender / Video Extender

Connection Pattern



Specification

Model Number	QSSM-3114 & QSSP-3114		
MAX. Resolution (4K@60Hz, 4:4:4)	3840x2160, 2560x1440, 1920x1080		
	3840x1600, 3440x1440, 2560x1080		
	3840x1080, 2048x2048, 1536x2048		
Interfaces	PC Side	Console Side	
Video Switching	QSSM-3114	HDMI 2.0 x 4 (In)	HDMI 2.0 x 1 (Out)
	QSSP-3114	4K DP x 4 (In)	HDMI 2.0 x 1 (Out) 4K DP x 1 (Out)*
USB 3.2 Switching (5Gbps)	USB 3.2-B x 4	USB 3.2-A x 1 USB HID-A x 3	
Audio Switching	SPK x 4 (In)	SPK x 1 (Out)	
Control Methods	Hotkey Control, Serial Control Keypad IN, Front Push Buttons		
Video Output Scaling	Auto, User Define 4K@30Hz, 1080P		
Seamless Switching	Zero Latency		
Serial Control	RJ-11 x 1 (19200bps) (8-Selections, 9600~115200bps) USB-C x 1		
Push Buttons	Port-Select x 4, Function x 4		
Hot Plug-and-Play	Yes		